



## **NSG 3060A**

# **THE MODULAR SOLUTION FOR 6 kV APPLICATIONS**



- **One box solution system**
- **Surge voltage up to 6.6 kV allows overtesting**
- **Easy to use 7" color touch screen**
- **IEC and ANSI coupling methods**
- **Parameters can be changed while test is running**
- **Wide range of optional test accessories**
- **High accuracy switching technology meets ANSI coupling requirements**

Teseq's new NSG 3060A conducted immunity generator takes the proven, user-friendly design of the highly successful NSG 3000 series to a new level. This innovative design uses modular architecture to provide a versatile system that can be configured for basic testing needs and expanded to meet the needs of sophisticated test laboratories.

**Designed to fulfill requirements for CE mark and ANSI C62.41 testing**, the NSG 3060A performs tests for Combination wave surge, Ring wave and Electrical Fast Transient (EFT) pulses as well as Power Quality Testing (PQT). Extensive expansion capabilities enable the system to be configured for a much broader range of applications.

**Using state of the art components**, the self-contained modules set new standards with respect to switching and phase accuracy and exceed the existing standards' requirements. With its powerful processors, the NSG 3060A can completely fulfill the unique coupling requirements specified by ANSI C62.41. This standard requires that the pulse amplitude be adjusted for the phase position of the pulse on the AC mains, and for the amplitude of the mains voltage.

**A 7" touch panel display with superb contrast and color** is the most striking feature of the new NSG 3060A. For fast and efficient data entry, input devices include an integrated keyboard and a thumbwheel with additional keys for sensitivity adjustment.

**The user-friendly graphic display speeds test setup.** Each parameter's value is highly visible, and all settings can be quickly selected and modified with the generously sized touch input buttons. A stylus is not necessary, and ramp functions are programmed quickly and easily. Multi-step test procedures can be created and their sequence or parameter values changed easily.

**The users can make manual parameter changes** using the thumbwheel while a test is under way, providing an effective and fast method for identifying critical threshold values. The Test Assistance (TA) function allows users to initiate standardized test with just a few "clicks" to achieve quick, reliable results in a development environment.

**The NSG 3060A has an Ethernet port for external PC control.** The Windows-based control software simplifies test programming and allows compilation of complex test sequences with diverse pulse types. Test reports can be generated during the test operation, allowing the operator to enter observations as the test progresses and increasing the efficiency of long-term tests.

## NSG 3060A

# THE MODULAR SOLUTION FOR 6 KV APPLICATIONS

| Model          | EFT/Burst | Surge | PQT | Ring wave | Telecom-Surge |
|----------------|-----------|-------|-----|-----------|---------------|
| NSG 3060A-IEC  |           |       |     |           |               |
| NSG 3060A-ANSI |           |       |     |           |               |
| NSG 3060A-FULL |           |       |     |           |               |

The NSG 3060A performs tests according to the following specifications:

### Combination wave pulse 1, 2/50 - 8/20 $\mu$ s (Hybrid-Surge pulse)

Pulse conforms to IEC/EN 61000-4-5 and ANSI (IEEE) 62.41

| Parameter                      | Value   |
|--------------------------------|---|
| Pulse voltage (open circuit):  | $\pm 200$ V to 6.6 kV (in 1 V steps)              |
| Pulse current (short circuit): | $\pm 100$ A to 3.3 kA                             |
| Impedance:                     | 2/12 $\Omega$                                     |
| Polarity:                      | positive / negative / alternate                   |
| Pulse repetition:              | 10 s* up to 9'999 s (in 1 s steps)                |
| Test duration:                 | 1 to 99'999 pulses, continuous                    |
| Phase synchronization:         | asynchronous, synchronous 0 to 359° (in 1° steps) |
| Coupling:                      | ANSI / IEC / external                             |

\* Repetition rate depends on voltage:

200 to 4400 V = 10 s repetition time

4401 to 6600 V = 20 s repetition time

### Ring wave 0.5 $\mu$ s/100 kHz

Pulse conforms to IEC/EN 61000-4-12 and ANSI (IEEE) C62.41

| Parameter                      | Value  |
|--------------------------------|--|
| Pulse voltage (open circuit):  | $\pm 200$ V to 6.6 kV (in 1 V steps)   |
| Pulse current (short circuit): | $\pm 16.6$ to $\pm 550$ A, $\pm 10\%$<br>$\pm 6.6$ to $\pm 220$ A, $\pm 10\%$<br>$\pm 1$ to $\pm 33$ A, $\pm 10\%$ |
| Impedance:                     | 12/30 $\Omega$   |
| Polarity:                      | positive / negative / alternate  |
| Pulse repetition:              | 10 s* up to 9'999 s (in 1 s steps)   |
| Test duration:                 | 1 to 99'999 pulses, continuous   |
| Phase synchronization:         | asynchronous, synchronous 0 to 359° (in 1° steps)  |
| Coupling:                      | ANSI / IEC / external  |

\* Repetition rate depends on voltage:

200 to 4400 V = 10 s repetition time 4401

to 6600 V = 20 s repetition time

## NSG 3060A

# THE MODULAR SOLUTION FOR 6 KV APPLICATIONS

### Burst (EFT) 5/50 ns

Pulse conforms to IEC/EN 61000-4-4

| Parameter              | Value   |
|------------------------|---|
| Pulse amplitude:       | ±200 V to 4.8 kV (in 1 V steps) - open circuit<br>±100 V to 2.4 kV (50 Ω matching system) |
| Burst frequency:       | 100 Hz to 1000 kHz  |
| Polarity:              | positive / negative / alternate   |
| Repetition time:       | 10 ms to 9'999 ms   |
| Burst time:            | 0.01 ms to 9'999 ms, single pulse   |
| Test duration:         | 1 s to 9'999s, 1 min to 1600 min, endless   |
| Phase synchronization: | asynchronous, synchronous 0 to 359° (in 1° steps)   |
| Coupling:              | internal / external   |

### Dips & Interrupts

conforms to IEC / EN 61000-4-11, IEC / EN 61000-4-29

| Parameter                       | Value   |
|---------------------------------|---|
| Dips & Interrupts:              | From EUT voltage input to 0 V, 0% <sup>(1)</sup>  |
| Uvar with optional variac:      | depending on model (VAR 3005A)                    |
| Uvar with step transformer:     | 0, 40, 70, 80% (INA 650xA)                        |
| Peak inrush current capability: | > 500 A (at 230 V)                                |
| Switching times:                | 1 to 5 μs (100 Ω load)                            |
| Event time (T-Event):           | 20 μs to 9999 s, 0.5 to 9'999 cycles              |
| Repetition time:                | 10 ms to 9'999 ms, 1 to 9'999 s                   |
| Test duration:                  | 1 to 99'999 events, endless                       |
| Phase synchronization:          | asynchronous, synchronous 0 to 359° (in 1° steps) |

(1) In combination with VAR 3005A-S16, effective minimal dip voltage ~8 V. As specified in IEC 61000-4-11, chapter. 5.1 a test voltage level from 0% to 20% of the rated voltage is considered as a total interruption.

## NSG 3060A

# THE MODULAR SOLUTION FOR 6 KV APPLICATIONS

### Variation test (with VAR 3005A-S16 only)

| Parameter                                | Value  |
|--|--|
| Uvar with optional variac:               | up to 265 V (in 1 V steps) or up to 115% U <sub>in</sub> (in 1% steps) |
| Decreasing time T <sub>d</sub> :         | 1 ms to 9.999 ms, 0.5 to 9999 cycles, abrupt                           |
| Time at reduced voltage T <sub>s</sub> : | 1 ms to 9.999 ms, 0.5 to 9999 cycles,                                  |
| Increasing time T <sub>i</sub> :         | 1 ms to 9.999 ms, 0.5 to 9999 cycles,                                  |
| Repetition time:                         | 1 s to 9'999 s   |
| Events:                                  | 1 to 99'999  |

### Pulsed magnetic field in conjunction with MFC 30

conforms to IEC/EN 61000-4-9

| Parameter                | Value   |
|--------------------------|---|
| Field:                   | 100 to 1200 A/m                                   |
| Polarity:                | positive / negative / alternate                   |
| Repetition time:         | 10 s to 9999s (in 1 s steps)                      |
| Impedance:               | 2 Ω   |
| Coil / impedance factor: | 0.01 to 100.00                                    |
| Test duration:           | 1 to 9'999 pulses, endless                        |
| Phase synchronization:   | asynchronous, synchronous 0 to 359° (in 1° steps) |

### Power magnetic field in conjunction with MFT 30 or MFO 6501A and MFC 30 / MFC 300

conform to IEC/EN 61000-4-8

| Parameter      | Value                             |
|----------------|-----------------------------------|
| Field:         | 1 to max. 40 A/m (in 1 A/m steps) |
| Frequency:     | 50/60 Hz                          |
| Coil factor:   | 0.01 to 99.99                     |
| Test duration: | 1 to 9'999 pulses, continuous     |

## NSG 3060A

# THE MODULAR SOLUTION FOR 6 KV APPLICATIONS

### Internal coupling network

| Parameter                 | Value  |
|---------------------------|--|
| EUT supply:               | 1-phase  |
| EUT VAC:                  | Up to 300 Vrms *, 50 / 60 Hz (phase - neutral)   |
| EUT VDC:                  | Up to 300 VDC  |
| EUT current               | 1 x 16 Arms continuous (over heat protected)   |
| Connections: Front panel: | - EUT: 4mm banana plug<br>- Burst OUT 50 $\Omega$ SHV<br>- Trigger out BNC   |
| Rear panel                | - EUT supply: banana plug 4 mm<br>- Additional ground connector<br>- Instrument supply 85 V to 264 VAC<br>- Connector surge HV – COM |
| Surge                     | Standard coupling as per IEC 61000-4-5   |
| Coupling mode             | Line to Line<br>Line(s) to ground  |
| Mains decoupling:         | 1.5 mH 0% + 35%  |
| Decoupling attenuation:   | Residual pulse voltage on EUT power supply inputs 15 % max.<br>Residual voltage on non-pulsed EUT power supply inputs 15 % max.      |
| EFT (Burst)               | Standard coupling all lines to ref ground (GND)<br>IEC / EN 61000-4-4<br>L, N, PE to ref GND   |
| PQT:                      | Dips & interrupts to phase L   |

## NSG 3060A

# THE MODULAR SOLUTION FOR 6 KV APPLICATIONS

### Technical specification

|                          |   |
|--------------------------|---|
| Instrument supply        | 85 to 265 VAC, 50 / 60 Hz                 |
| Dimensions NSG 3060A-IEC | 19"; 6 HU, 448 x 289 x 500 mm (W x H x D) |
| Weight NSG 3060A         | 30 kg (66 lbs)                            |

### Options

|                 |   |
|-----------------|---|
| CDN 3063A-C32   | Three phase 480 V / 32 A automatic coupling decoupling networks for Burst/EFT up to 4.8 kV, Surge, Ring Wave pulses up to 6,6 kV      |
| CDN 3063A-C63   | Three phase 480 V / 63 A automatic coupling decoupling network for Burst/EFT up to 4.8 kV, Surge, Ring Wave pulses up to 6,6 kV       |
| CDN 3063A-C100  | Three phase 480 V / 100 A automatic coupling decoupling network for Burst/EFT up to 4.8 kV, Surge, Ring Wave pulses up to 6,6 kV      |
| CDN 3425        | Burst EFT capacitive coupling clamp for data line coupling per IEC 61000-4-4  |
| CDN 117A-C6-4-1 | Coupling networks for unsymmetrical signal-/data lines (surge)  |
| CDN 118A-C6-4-1 | Coupling networks for symmetrical signal-/data lines (surge)  |
| CDN HSS-2       | Coupling network for 2 kV surge pulse 1.2 / 50 $\mu$ s IEC/EN 61000-4-5 on unshielded symmetrical high speed telecom lines (Ethernet) |
| PVF BKIT 1      | Burst/EFT verification set  |
| MD 210          | Voltage differential probe 7 kV common / differential 1000:1 / 100:1  |
| MD 300          | Current probe 5 kA  |

### Accessories for IEC/EN 61000-4-11

|               |   |
|---------------|---|
| TVT 1-250-16  | Manual step transformer, 16 AAC, 0/40/70/80%    |
| VAR 3005A-S16 | Automatic single variable transformer, 1 x 16 A |

### Accessories for IEC/EN 61000-4-8/-4-9

|           |   |
|-----------|---|
| MFO 6501A | Manual magnetic field option -4-8   |
| MFC 30    | Magnetic field coil 1 x 1 m, with MFO max. 40 A/m -4-8; Surge* max. 1200 A/m -4-9 |
| MFC 300   | Magnetic field coil 1 x 1 m; max. 330 A/m -4-8                                    |

AMETEK CTS GmbH  
Sternenhofstrasse 15 4153 Reinach Switzerland

© November 2018 AMETEK CTS  
Specifications subject to change without notice. This product is designed and manufactured under the strict quality and environmental requirements of the ISO 9001. This document has been carefully checked. However, AMETEK CTS does not assume any liability for errors or inaccuracies.

691-388 A December 2018